# **ProSense Basic M18 Inductive Proximity Sensors**



#### **Basic Series Inductive Proxes M18 (18mm)**


- Operating distance 5 to 8mm
- · Nickel-plated brass housing
- LCP (Liquid Crystal Polymer) active face
- Normal range operating distance
- Cable or M12 connector
- PNP or NPN, N.O. or N.C.
- IP67 protection




Basic M18 Inductive Proximity Sensor Selection Chart										
Part Number	Price	Sensing Range	Mounting	Output State	Logic	Connection	Wiring	Drawing Link		
Standard Distance	Standard Distance									
PBK6-AP-1A	\$12.00	5mm [0.20 in]	Flush	N.O.	PNP	Cable, 3 pole, 2m [6.5 ft]	Diagram 1	PDF		
PBK6-AP-1H	\$13.00	5mm [0.20 in]	Flush	N.O.	PNP	4-pin M12 connector	Diagram 3	PDF		
PBK6-CP-1H	\$13.00	5mm [0.20 in]	Flush	N.C.	PNP	4-pin M12 connector	Diagram 3	<u>PDF</u>		
PBK6-AN-1H	\$13.00	5mm [0.20 in]	Flush	N.O.	NPN	4-pin M12 connector	Diagram 4	PDF		
PBK6-AP-2A	\$12.00	8mm [0.31 in]	Non-flush	N.O.	PNP	Cable, 3 pole, 2m [6.5 ft]	Diagram 1	PDF		
PBK6-AP-2H	\$13.00	8mm [0.31 in]	Non-flush	N.O.	PNP	4-pin M12 connector	Diagram 3	PDF		
PBK6-CP-2H	\$13.00	8mm [0.31 in]	Non-flush	N.C.	PNP	4-pin M12 connector	Diagram 3	PDF		
PBK6-AN-2H	\$13.00	8mm [0.31 in]	Non-flush	N.O.	NPN	4-pin M12 connector	Diagram 4	PDF		

### **Wiring Diagrams**

## Diagram 1 PNP Cable Version




## Diagram 2 NPN Cable Version




## Connector M12 connector



## Diagram 3 PNP M12 Connector




## Diagram 4 NPN M12 Connector



# ProSense Basic M18 Inductive Proximity Sensors

Basic M18 Inductive	Basic M18 Inductive Proximity Sensor Specifications					
Mounting Type	Flush	Non-flush				
Nominal Sensing Distance	5mm [0.20 in]	8mm [0.31 in]				
Material Correction Factors	See the Materia	l influence table				
Output Type	NPN or PNP/N.0	D. or N.C./3-wire				
Operating Voltage	10 to 3	0 VDC				
No-load Supply Current	≤ 10	)mA				
Operating (Load) Current	200	mA				
Off-state (Leakage) Current	≤ 10	)mA				
Voltage Drop	≤ 1.8 V [I	=100mA]				
Switching Frequency	100	0Hz				
Hysteresis	< 1	0%				
Repeat Accuracy	< 3%					
Ripple	< 10%					
Time Delay Before Availability (tv)	< 50	ms				
Reverse Polarity Protection	Ye	es				
Short-Circuit Protection	Yes (auto-reset)					
Operating Temperature	-25 to 70°C [-13 to 158°F]					
Protection Degree (DIN 40050)	IP67					
Indication/Switch Status	Yellow, on wh	nen detecting				
Housing Material	Nickel-pla	ted brass				
Sensing Face Material	LCP (Liquid Crystal Polymer)					
Shock/Vibration	See <u>Proximity Se</u>	nsor Terminology				
Tightening Torque	See Torque Table below					
Weight	145g [5.11 oz] (cable version) -	95g [3.35 oz] (M12 connector)				
Connection	2m [6.5 ft] PUR Cable, 3 pole	e, 26AWG or M12 Connector				
Agency Approvals	CE cULus	E328811				

Installation Tightening Torque				
Mounting	Flush, non-flush mountable			
Housing Material	Nickel plated brass			
Diameter	18mm [0.71 in]			
Tightening Torque for A (A = 11mm [0.43 in])	20 N•m [14.75 lb•ft]			
Tightening Torque for B	30 N•m [22.13 lb•ft]			





#### Flush Mounting

Flush models can be installed with their sensing faces flush to the metal. The distance from opposing metal surfaces must be  $\geq 3$ sn (where sn=nominal switching distance), and the distance between two proximity switches (side by side) must be  $\geq 2$ D.

#### Non-Flush Mounting

Non-flush models can be identified by their "caps," since they have no metal housing surrounding the area of the sensing face. The sensing face must extend  $\geq 2$ sn (where sn=nominal switching distance) from the metallic installation medium. The distance from opposing metal surfaces must be  $\geq 3$ sn, and the distance between two adjacent proximity switches must be  $\geq 3$ D. The metal body leaves uncovered part of the sensing area, resulting in an increased sensing distance.





**Proximity Sensors** 

## **Accessories for 18mm Sensors**

#### **Axial Mounting Bracket**

Axial mounting bracket available in zinc plated steel or 316L stainless steel. Has two mounting holes (use 4mm screws) and allows for rotation of an optical axis for right-beam-angle-adapter sensors. Hexagonal nuts not included. For use with 18mm sensors.


Accessories for 18mm Sensors						
Part Number	Weight lb [g]					
<u>ST18A</u>	\$2.00	Micro Detectors mounting bracket, axial, zinc plated steel. For use with 18mm sensors.	0.06 [27.2]			
<u>ST18A7W</u>	\$7.25	Micro Detectors mounting bracket, axial, 316L stainless steel. For use with 18mm sensors.	0.06 [27.2]			



**ST18A** 

#### **Dimensions**

mm [inches]



#### **Right-angle Mounting Bracket**


Right-angle mounting bracket for use with 18mm sensors. Has two mounting holes (use 4mm screws) and allows the rotation of an optical axis for axial sensors. Hexagonal nuts not included.

Accessories for 18mm Sensors						
Part Number	Part Number Price Description					
ST18C	\$2.00	Micro Detectors mounting bracket, right-angle, zinc plated steel. For use with 18mm sensors.	0.06 [27.2]			
<u>ST18C7W</u>	\$7.25	Micro Detectors mounting bracket, right-angle, 316L stainless steel. For use with 18mm sensors.	0.06 [27.2]			



#### **Dimensions**

mm [inches]



## **Accessories for 18mm Sensors**

### **Right-angle Mounting Brackets**

Mounting bracket, right-angle, fixed insertion stop adjustment, plastic. For use with 18mm sensors. Available with or without fixed insertion stop.

	Accessories for 18mm Sensors							
Part Number	Part Number Price Description		Drawing Link	Weight lb [g]				
<u>OPT2104</u>	\$10.50	Wenglor mounting bracket, right-angle, fixed insertion stop adjustment, plastic. For use with 18mm sensors.	PDF	0.06 [27.2]				
<u>OPT2105</u>	\$10.50	Wenglor mounting bracket, right-angle, plastic. For use with 18mm sensors.	<u>PDF</u>	0.06 [27.2]				



OPT2104, OPT2105

#### **Right-angle Swivel Mounting Systems**

Mounting bracket, right-angle swivel, 360 degree vertical and horizontal adjustment, 12mm rod mount. For use with 18mm sensors. Available in all 304 stainless steel or with an aluminum head and a stainless steel mounting plate.

	Accessories for 18mm Sensors							
Part Number	Price	Description	Mounting Head	Mounting Plate	Drawing Link	Weight lb [g]		
<u>OPT2116</u>	\$11.50	Wenglor mounting bracket, right-angle swivel, 360 degree vertical and horizontal adjustment, aluminum, 12mm rod mount. For use with 18mm sensors.	Aluminum	304 Stainless steel	<u>PDF</u>	0.15 [68.0]		
<u>OPT2117</u>	\$21.00	Wenglor mounting bracket, right-angle swivel, 360 degree vertical and horizontal adjustment, 304 stainless steel, 12mm rod mount. For use with 18mm sensors.	304 Stainless steel	304 Stainless steel	<u>PDF</u>	0.28 [127.0]		



OPT2116, OPT2117

Note: 304 Stainless steel mounting rods sold separately: <u>OPT2109</u> (200mm [7.87 in] length), <u>OPT2110</u> (300mm [11.81 in] length), and <u>OPT2111</u> (500mm [19.69 in] length).

www.automationdirect.com

## **Mounting Rods and Brackets**

#### **Mounting Rods**

304 Stainless steel rods for mounting swivel brackets <u>OPT2112</u> - <u>OPT2127</u> Available in three lengths: 200mm, 300mm, and 500mm. 12mm diameter.

M	Mounting Rods for OPT2112-2127 Swivel Mounting Brackets								
Part Number	Price	Description	Drawing Link	Weight Ib (g)					
<u>OPT2109</u>	\$13.00	Wenglor mounting rod, 12mm diameter, 200mm length, 304 stainless steel.	PDF	0.41 [185.97]					
<u>OPT2110</u>	\$16.00	Wenglor mounting rod, 12mm diameter, 300mm length, 304 stainless steel.	PDF	0.60 [272.16]					
<u>OPT2111</u>	\$21.00	Wenglor mounting rod, 12mm diameter, 500mm length, 304 stainless steel.	PDF	0.98 [444.52]					



### **Right-angle Mounting Bracket**

Mounting bracket, right-angle, nickel-plated brass. For use with 12mm mounting rods OPT2109, OPT2110 & OPT2111.

Right-angle Mounting Brackets for 12mm Sensors								
Part Number	Part Number Price Description							
<u>OPT2108</u>	\$16.00	Wenglor mounting bracket, right-angle, nickel-plated brass. For use with 12mm mounting rods OPT2109, OPT2110 & OPT2111.	<u>PDF</u>	0.07 [31.8]				



www.automationdirect.com