

USB to RS-485 PC Adapter

USB-485M \$60.00

Convenient 2-wire USB to RS-485 serial communication adapter for universal RS-485 use (GS drives, SureServo servos, Solo temperature controllers, CLICK PLCs, etc.). Does not require an external power supply or complicated configuration process.

Features:

- Type A (plug) USB connector
- Universal female RJ45/RJ12 modular connector (accepts RJ12 & RJ45 plugs)
- Supports multiple baud rates
- USB v2.0 compliant
- RoHS compliant
- CE compliant

Components Included:

- Adapter
- Cable – 6-wire RJ12 crossover; 2m [79 in] (for plug & play connectivity to GS drives)
- Cable – 2-wire RJ12–flying leads; 2m [79in] (for universal RS-485 connectivity to SureServo, Solo, etc.)


Specifications	
Description	USB TO RS-485 PC Adapter; includes (2) RJ12 cables, mini-CD with driver, instructions
Component Compatibility *	GS series AC drives – GS-OFT configuration software GS series AC drives – Modbus polling SureServo servo drives – SV-PRO configuration software** SureServo servo drives – Modbus polling** SOLO process controllers – SL-SOFT configuration software SOLO process controllers – Modbus polling CLICK PLCs – Modbus polling Productivity PLCs – Modbus polling
Power Supply	No external power supply needed
Power Consumption	0.4 W
Voltage Isolation	3000 VDC
Baud Rates Supported	75, 150, 300, 600, 1200, 2400, 4800, 9600, 19200, 38400, 57600, 115200 (bps)
Transmission Type	RS-485 half-duplex (2-wire)
LED Display	Steady Green LED ON: power is ON. Blinking orange LED: data is transmitting.
USB Connector	Type A (plug)
RS-485 Connector	RJ45
Compatibility	USB v2.0 specification
PC Compatibility	Windows Operating System required for bridge & driver installation: 32-bit driver: Windows 7, 8, 8.1, 10 64-bit driver: Windows 7, 8, 8.1, 10

* NOT compatible with DirectSOFT PLC software. (DirectSOFT RS-485 programming requires 4-wire full-duplex data transmission.)
** Requires SVC-485CFG-CBL-2 cable.

USB-485M



USB-485M Dimensions



USB-485M RJ-45 Pin-out



8 ← 1



RJ-45

Pinout	
Pin	Description
1	reserved
2	reserved
3	reserved
4	SG+
5	SG-
6	reserved
7	reserved
8	reserved