


Wiring diagram for 9 pole D-Sub connector

CONNECTOR D-Sub 9 PIN PRE-WIRED



Electric contact position	Color conductor cable	Function	4-position base	8-position base
1	White	1 + VDC	Solenoid pilot 14 valve 1	Solenoid pilot 14 valve 1
2	Brown	2 + VDC	Solenoid pilot 14 valve 2	Solenoid pilot 12 valve 1
3	Green	3 + VDC	Solenoid pilot 14 valve 3	Solenoid pilot 14 valve 2
4	Yellow	4 + VDC	Solenoid pilot 14 valve 4	Solenoid pilot 12 valve 2
5	Grey	5 + VDC	/	Solenoid pilot 14 valve 3
6	Pink	6 + VDC	/	Solenoid pilot 12 valve 3
7	Blue	7 + VDC	/	Solenoid pilot 14 valve 4
8	Red	8 + VDC	/	Solenoid pilot 12 valve 4
9	Black	COM 0VDC	Common	Common