D0-06DR-D Cut Sheet





DirectLOGIC DL06 PLC, 12-24 VDC required, serial ports, Discrete Input: 20-point, DC, Discrete Output: 16-point, relay.

For complete product information, please see this item on our store at the following link:



https://www.automationdirect.com/pn/D0-06DR-D

Technical Specifications

| reenned opeened ons | |
|---|---|
| Brand | DirectLOGIC |
| Item | PLC |
| Series | DL06 |
| Total Memory | 14.8k words |
| Ladder Memory | 7k words |
| User Data Memory | 7k words |
| Programming Language | Ladder |
| Programming Software | DirectSOFT programming software v4.0 or later |
| Communication Port and Connection Type(s) | (1) RS-232 (RJ12) (1) RS-232/RS-422/RS-485 (DB15HD female) |
| Port Protocol(s) | DirectNET Modbus RTU ASCII K-sequence programming and monitoring |
| Port Speed(s) | fixed at 9.6k baudup to 38.4k baud |
| Real Time Clock/Calendar | Yes |
| Retentive Memory | Yes |
| Battery Backup | Yes |
| Maximum Expansion Modules Allowed | 4 |
| External Power Requirement | 12-24 VDC |
| Number of Discrete Input Points | 20 |
| Nominal Input Voltage | 12-24 VDC |
| Voltage Type | DC |
| Discrete Input Type | Sinking/sourcing |
| Number of Isolated Discrete Input Commons | 5 |
| Number of Points per Discrete Input Common | 4 |
| Frequency Response | 7 kHz |
| Number of Discrete Output Points | 16 |

| Nominal Output Voltage | 6-24 VDC/6-240 VAC |
|--|--|
| Discrete Output Type | Relay |
| Relay Configuration | (16) Form A (SPST) relays |
| Load Current | 2A/point |
| Number of Isolated Discrete Output Commons | 4 |
| Number of Points per Discrete Output Common | 4 |
| Maximum Number of PID Loops | 8 |
| Number of High-Speed Capable Input Points | 4 |
| High-Speed Counter(s) | up to (2) up counters up to (1) down counter up to (1) up/down counter up to (1) quadrature (A and B) counter |
| Position Scaling | up to (2) up counters up to (1) down counter up to (1) up/down counter up to (1) quadrature (A and B) counter |
| Frequency Measurement | up to (2) up counters up to (1) down counter up to (1) up/down counter up to (1) quadrature (A and B) counter |
| Interrupt(s) | up to (1) input interruptup to (1) timer interrupt |
| Additional Information | Purchase D2-BAT-1 backup battery separately |

Agency Approvals

| E157382 | |
|------------------------|--|
| None | |
| E200031 | |
| View CE declarations | |
| None | |
| Yes (See CE Doc) | |
| View EU REACH document | |
| | |

Dimensional Drawings



2D Drawing PDF Link: https://cdn.automationdirect.com /static/drawings/D0-06DR-D.pdf See store item page for other formats.