# **Shields**

## P1AM-ETH \$55.00

#### **Ethernet Communications Shield**

The P1AM-ETH is a housed Arduino Compatible Ethernet Shield based on the Wiznet W5500 Ethernet Controller. It interfaces to the left side

of the <u>P1AM-100</u> CPU and most Arduino MKR form factor shields.



General Specifications		
Operating Temperature	0° to 60°C (32° to 140°F)	
Storage Temperature	-20° to 70°C (-4° to 158°F)	
Humidity	5 to 95% (non-condensing)	
Environmental Air	No corrosive gases permitted	
Vibration	IEC60068-2-6 (Test Fc)	
Shock	IEC60068-2-27 (Test Ea)	
Heat Dissipation	750mW	
Enclosure Type	Open Equipment	
Power Budget	150mA/5V	
Recommended Library	Arduino Ethernet	
Module Location	Connects to the left side of the P1AM-100 CPU.	
Weight	20g (0.8 oz.)	
Agency Approvals	UL 61010-1 and UL 61010-2-201 File E139594, Canada & USA CE	


### **Ethernet Features**

Supports Hardwired TCP Protocols:

- TCP, UDP, ICMP, IPV4, ARP, IGMP, PPPOE
- Supports 8 independent sockets simultaneously
- Supports Power Down Mode
- Supports Wake on LAN over UDP
- Supports High Speed Serial Peripheral Interface (SPI MODE 0, 3)
- Internal 32K bytes of Memory for TX/RX Buffers
- 10BaseT / 100BaseTX Ethernet PHY embedded
- Supports Auto Negotiation (Full and Half Duplex, 10 and 100-based)
- Does Not Support IP Fragmentation
- 3.3 V operation with 5V I/O signal tolerance
- LED outputs (Full / Half duplex, Link, Speed, Active)

## **!WARNING!**

Do not add or remove modules with field power applied!



Header Pins Used for Ethernet Shield			
Pins Used	Function	Description	
5	ETH SS		
8	MOSI		
9	SCK	SPI pins are shared with other devices on SPI bus	
10	MISO	dovides on or rods	

MKR Expansion Bus Pins		
<b>GPIO</b>	A0-A6, 0-14	
Analog Input Pins	A0–A6	
Analog Output Pins	A0	
PWM Pins	0–8, 10, A3, A4	
Interrupt Pins	0, 1, 4–8, A1, A2	
5V	5V supply output	
Vin	5V regulated supply	
vcc	3.3 V supply output	
GND	Ground	
RST	Reset	
AREF	Analog Input Reference	

#### **Critical Notes:**

Pins A3, A4, and 8–10 are used for the base controller.

Do not exceed 46mA combined from pins 0, 1, and 4-10.

Do not exceed 3.3 V on any I/O pin.

Do not exceed 7mA on any I/O pin.

Do not apply power to 5V or VCC