# NEMA 4 and 4X Extra Deep Stainless Steel Pushbutton



## **Applications**

- Designed to accept standard heavy duty oil-tight pushbuttons, switches and pilot lights.
- Provides protection from dirt, dust, oil, and water.

## Construction

- Smooth continuously welded seams.
- Welded brackets provide for enclosure mounting.
- Captive cover screws fasten into threaded, sealed wells.
- Larger enclosures provide internally hinged removable covers, designed to hold the cover open during wiring (see drawings).
- Oil-resistant gasket and adhesive.
- A bonding stud is provided on the door and a grounding stud is provided on the enclosure.



## Finish

• Natural stainless steel with a #4 smooth brushed finish.

## Listings

- UL 508A Type 4 and 4X [UL File E65324]
- CSA Type 4 and 4X
  [CSA File LR21001]
- Complies with
- NEMA Type 4 and 4X
- IEC 60529, IP66
- All appropriate components are required to maintain these standards.





NEMA 4 and 4X Extra Deep Stainless Steel Pushbutton												
3	04 Stainl	ess Steel		316 Stainless Steel				Console Size HxWxD	Drawing	#	Steel	Hinged
22 mm	Price	30 mm	Price	22 mm	Price	30 mm	Price		Link	Holes	Gauge	пшуеи
1437MSSA	\$216.00	<u>1437SSA</u>	\$211.00	<u>1437MS16A</u>	\$281.00	<u>1437S16A</u>	\$260.00	4.31 x 4.31 x 4.91 [109 x 109 x 125]	PDF	1	16	No
<u>1437MSSB</u>	\$265.00	<u>1437SSB</u>	\$258.00	<u>1437MS16B</u>	\$345.00	<u>1437S16B</u>	\$319.00	6.31 x 4.31 x 4.92 [160 x 109 x 125]	PDF	2		Yes
<u>1437MSSC</u>	\$307.00	<u>1437SSC</u>	\$299.00	<u>1437MS16C</u>	\$400.00	<u>1437S16C</u>	\$370.00	8.31 x 4.31 x 4.92 [211 x 109 x 125]	PDF	3	44	
1437MSSD	\$345.00	1437SSD	\$336.00	<u>1437MS16D</u>	\$451.00	<u>1437S16D</u>	\$416.00	10.31 x 4.31 x 4.92 [262 x 109 x 125]	PDF	4	14	
_	_	<u>1437SSS</u>	\$659.00	_	_	<u>1437S16S</u>	\$787.00	12.06 x 11.06 x 4.92 [306 x 281 x 125]	PDF	16		
Note: Dimensions in inches [millimeters].												

## **NEMA 4 and 4X Extra Deep Stainless Steel Pushbutton**





## **Dimensions**






#### 22 mm [0.87in] Hole Placement







### 30 mm [1.18in] Hole Placement

 $\langle \cap \rangle$  $\bigcirc$ 0  $\bigcirc$  $\bigcirc$  $\bigcirc$  $\bigcirc$  $\begin{array}{c} \circ \circ \circ \circ \\ \circ \circ \circ \circ \circ \\ \circ \circ \circ \circ \circ \end{array}$  $\bigcirc$  $\bigcirc$ Ó

