1-800-633-0405 For the lates **DM Series Photoelectric Sensors**



M12 (12mm) Metal with Teach Function - DC

- Metal housing
- Teach function available on diffuse and polarized reflective models
- Adjustable sensitivity on through-beam models
- Axial cable or M12 quick-disconnect models; purchase cable separately
- Multifunction LED status indicator
- Operates on 10-30 VDC
- IP67 rated




			DM Series	Photoelectr	ic Senso	rs Selection Ch	art		
Part Number		Price	Sensing Range	Output State	Logic	Connection	Wiring	Dimensions	Characteristic Curves
Diffuse									
DM3-0N-1A		\$47.00			NPN	2m [6.5 ft] axial cable	Diagram 1	Figure 1	Chart 1
DM3-0P-1A		\$47.00	Up to	N.O. + N.C.	PNP	2m [6.5 ft] axial cable	Diagram 2	Figure 1	Chart 1
DM3-0N-1H		\$47.00	100mm [3.9 in]	Selectable	NPN	M12 connector	Diagram 1	Figure 2	Chart 1
DM3-0P-1H		\$47.00			PNP	M12 connector	Diagram 2	Figure 2	Chart 1
DM7-0N-1A		\$47.00			NPN	2m [6.5 ft] axial cable	Diagram 1	Figure 1	Chart 2
DM7-0P-1A		\$47.00	Up to	N.O. + N.C.	PNP	2m [6.5 ft] axial cable	Diagram 2	Figure 1	Chart 2
DM7-0N-1H		\$47.00	300mm [11.8 in]	Selectable	NPN	M12 connector	Diagram 1	Figure 2	Chart 2
DM7-0P-1H		\$47.00			PNP	M12 connector	Diagram 2	Figure 2	Chart 2
Polarized Reflect	ive*								
DMP-0N-1A		\$55.00			NPN	2m [6.5 ft] axial cable	Diagram 1	Figure 1	Chart 3
DMP-0P-1A		\$55.00	Up to	N.O. + N.C.	PNP	2m [6.5 ft] axial cable	Diagram 2	Figure 1	Chart 3
DMP-0N-1H		\$55.00	2m [6.6 ft]	Selectable	NPN	M12 connector	Diagram 1	Figure 2	Chart 3
<u>DMP-0P-1H</u>		\$55.00			PNP	M12 connector	Diagram 2	Figure 2	Chart 3
Through-beam**	r					•			•
DMR-0N-1A	Receiver	\$40.00			NPN	2m [6.5 ft] axial cable	Diagram 1	Figure 1	Chart 4
DMR-0P-1A	Receiver	\$40.00			PNP	2m [6.5 ft] axial cable	Diagram 2	Figure 1	Chart 4
DMR-0N-1H Receiver		\$40.00	Up to	N.O. + N.C.	NPN	M12 connector	Diagram 1	Figure 2	Chart 4
DMR-0P-1H Receiver		\$40.00	4m [13.1 ft]	Selectable	PNP	M12 connector	Diagram 2	Figure 2	Chart 4
DME-00-1A	Emitter	\$32.00			Receiver	2m [6.5 ft] axial cable	Diagram 3	Figure 1	Chart 4
DME-00-1H	Emitter	\$32.00			dependent	M12 connector	Diagram 3	Figure 2	Chart 4

* Purchase reflectors separately. **Purchase one receiver and one emitter for a complete set.

Wiring Diagrams


Diagram 1 NPN Output



Diffuse models




Diagram 2 PNP Output



Polarized reflective models



Diagram 3 Emitter with check Input



2-meter Axial Cable version: check is black M12 Connector: check is Pin 2 (white)

Through-beam models

r-(+) Light-on WH/2 --¦ -- N.C. Dark-on └--- Dark-on

Connector

M12 connector

1-800-633-0405 **DM Series Photoelectric Sensors**

DM Se	ries Photoelectric Sen	sors Specifications					
Specifications	Diffuse Models	Reflective Models	Through-Beam Models				
Туре	Diffuse reflection	Polarized reflection ⁴	Through-beam⁵				
Sensing Distance	DM3:100mm ¹ DM7: 300mm ²	2m³	4m				
Light Spot Diameter	DM3: 80mm @ 100mm DM7: 200mm @ 300mm	100mm @ 2.5 m	350mm @ 4 m				
Emission	Infrared [880nm]	Red [660nm]	Infrared [880nm]				
Sensitivity	Teach function (see produ	uct data sheet for details)	Fixed				
Output Type	NF	PN or PNP - Light on / Dark on select	able				
Operating Voltage		10-30VDC					
No-load Supply Current	ad Supply Current ≤ 20mA						
Operating (Load) Current	≤ 100mA						
Off-state Leakage Current	≤ 10µA						
Voltage Drop	2V max at 100mA						
Switching Frequency	400	Hz	250Hz				
Ripple		≤ 10%					
Time Delay Before Availability (tv)		150ms					
Short-Circuit Protection	Yes	s, switch auto-resets after load is rem	oved				
Operating Temperature		-25 to 70°C [-13 to 158°F]					
Protection Degree (DIN 40050)		IEC IP67					
LED Indicators - Switching Status		Yellow					
Housing Material		Nickel-plated brass					
Lens Material		Polymethyl methacrylate (PMMA)					
Shock/Vibration		See terminology section					
Tightening Torque		10 N•m (7.37 lb-ft)					
Weight		Axial cable models: 54g [1.9 oz] M12 connector models: 18g [0.63 oz	z]				
Connectors	2m	[6.5 ft] axial cable; M12 [12mm] conr	nector				
Agency Approvals		cULus F187310, CE					

¹ With 100x100mm white matte paper

² With 200x200mm white matte paper ³ With standard Ø84mm <u>RL110</u> reflector


⁴ Purchase reflectors separately.

⁵ An emitter (DME) and receiver (DMR) pair must be ordered for a complete sensor set.

To obtain the most current agency approval information, see the Agency Approval Checklist section on the specific part number's web page.


Dimensions





(Diffuse and Reflective only)

Switching Element Function							
Through-beam and Diffuse Reflective Reflective Models Models							
Light-on	N.C.	N.O.					
Dark-on	N.O.	N.C.					



1-800-633-0405 For the latest **DM Series Photoelectric Sensors**

Characteristic curves

Chart 1 (Diffuse DM3)




Chart 2 (Diffuse DM7)




Chart 3 (Polarized reflective)







Chart 4 (Through-beam)


Excess gain




Parallel displacement









Parallel displacement





WARNING: THESE PRODUCTS ARE NOT SAFETY SENSORS AND ARE NOT SUITABLE FOR USE IN PERSONAL SAFETY APPLICATIONS.



Accessories for 12mm Sensors

Axial Mounting Bracket

Mounting bracket, axial, available in zinc-plated steel or 316L stainless steel. For use with 12mm sensors. Has two mounting holes (use 3mm screws) and allows the rotation of an optical axis for right-angle adapter sensors. Hexagonal nuts not included.

	Accessories for 12mm Sensors									
Part Number	Price	Description	Drawing Link	Weight Ib [g]						
<u>ST12A</u>	\$2.00	Micro Detectors mounting bracket, axial, zinc plated steel. For use with 12mm sensors.	PDF	0.03 [13.6]						
<u>ST12A7W</u>	\$7.25	Micro Detectors mounting bracket, axial, 316L stainless steel. For use with 12mm sensors.	PDF	0.03 [13.6]						



<u>ST12A</u>

Right-angle Mounting Bracket

Mounting bracket, right-angle, zinc-plated steel or 316L stainless steel. For use with 12mm sensors. Has two mounting holes (use 3mm screws) and allows the rotation of an optical axis for axial sensors. Hexagonal screws not included.

	Accessories for 12mm Sensors									
Part Number Price Description Drawing Link Weigh Ib [g]										
<u>ST12C</u>	\$2.00	Micro Detectors mounting bracket, right-angle, zinc plated steel. For use with 12mm sensors.	<u>PDF</u>	0.03 [13.6]						
<u>ST12C7W</u>	\$7.25	Micro Detectors mounting bracket, right-angle, 316L stainless steel. For use with 12mm sensors.	<u>PDF</u>	0.03 [13.6]						



<u>ST12C</u>

Accessories for 12mm Sensors

Right-angle Fine Tune Mounting Bracket

Mounting bracket, right-angle, fine tune vertical and horizontal adjustment, nickel-plated steel. For use with 12mm sensors. Enables fine tuning vertical and horizontal placement.

Accessories for 12mm Sensors									
Part Number Price Description Drawing Link									
<u>OPT2035</u>	PT2035 \$38.50 Wenglor mounting bracket, right-angle, fine tune vertical and horizontal adjustment, nickel plated steel. For use with 12mm sensors.		<u>PDF</u>	0.16					



OPT2035

Accessories for 12mm Sensors

Right-angle Mounting Brackets

Mounting bracket, right-angle, fixed insertion stop adjustment, plastic. For use with 12mm sensors. Available with or without fixed insertion stop.

	Accessories for 12mm Sensors									
Part Number	Part Number Price Description									
<u>OPT2102</u>	\$8.00	Wenglor mounting bracket, right-angle, fixed insertion stop adjustment, plastic. For use with 12mm sensors.	PDF	0.05 [22.7]						
<u>OPT2103</u>	\$8.00	Wenglor mounting bracket, right-angle, plastic. For use with 12mm sensors.	<u>PDF</u>	0.05 [22.7]						



Right-angle Swivel Mounting Systems

Mounting bracket, right-angle swivel, 360 degree vertical and horizontal adjustment, 12mm rod mount. For use with 12mm sensors. Available in all stainless steel or with an aluminum head and stainless steel mounting plate.

	Accessories for 12mm Sensors											
Part Number	Price	Description	Mounting Head	Mounting Plate	Drawing Link	Weight Ib [g]						
<u>OPT2114</u>	\$11.50	Wenglor mounting bracket, right-angle swivel, 360 degree vertical and horizontal adjustment, aluminum, 12mm rod mount. For use with 12mm sensors.	Aluminum	Stainless steel	<u>PDF</u>	0.14 [63.5]						
<u>OPT2115</u>	\$21.00	Wenglor mounting bracket, right-angle swivel, 360 degree vertical and horizontal adjustment, 304 stainless steel, 12mm rod mount. For use with 12mm sensors.	304 Stainless steel	304 Stainless steel	<u>PDF</u>	0.27 [122.5]						



Note: 304 stainless steel mounting rods sold separately: <u>OPT2109</u> (200mm [7.87 in] length), <u>OPT2110</u> (300mm [11.81 in] length), and <u>OPT2111</u> (500mm [19.69 in] length).

OPT2114, OPT2115

1-800-633-0405 Mounting Rods and Brackets

Mounting Rods

304 Stainless steel rods for mounting swivel brackets <u>OPT2112</u> - <u>OPT2127</u> Available in three lengths: 200mm, 300mm, and 500mm. 12mm diameter.

M	Mounting Rods for OPT2112-2127 Swivel Mounting Brackets										
Part Number	Part Number Price Description										
<u>OPT2109</u>	\$13.00	Wenglor mounting rod, 12mm diameter, 200mm length, 304 stainless steel.	PDF	0.41 [185.97]							
<u>OPT2110</u>	\$16.00	Wenglor mounting rod, 12mm diameter, 300mm length, 304 stainless steel.	PDF	0.60 [272.16]							
<u>OPT2111</u>	\$21.00	Wenglor mounting rod, 12mm diameter, 500mm length, 304 stainless steel.	PDF	0.98 [444.52]							



Right-angle Mounting Bracket

Mounting bracket, right-angle, nickel-plated brass. For use with 12mm mounting rods <u>OPT2109</u>, <u>OPT2110</u> & <u>OPT2111</u>.

Right-angle Mounting Brackets for 12mm Sensors									
Part Number	Part Number Price Description								
<u>OPT2108</u>	\$16.00	Wenglor mounting bracket, right-angle, nickel-plated brass. For use with 12mm mounting rods OPT2109, OPT2110 & OPT2111.	<u>PDF</u>	0.07 [31.8]					




1-800-633-0405 Reflectors

RL Series Reflectors for Polarized Reflective Photoelectric Sensors (All Models)

- Suitable for use with polarized light photoelectric sensors
- Shapes and sizes for most applications
- Miniature types for close mounting in multiple sensor installations
- Single hole, dual hole and self-adhesive mounting types available
- Single and 10-packs available

Installation Notes

- Keep the reflector surface clean to ensure peak detection performance. This is especially true when the maximum sensing range is being used. Clean using a damp cloth.
- When selecting a reflector, it is important to consider the ambient conditions it will be exposed to. Dusty or high humidity conditions may reduce the sensing range as much as 90%.
- Reflectors should be positioned at a 90° angle to the optical axis with a tolerance of $\pm 15^{\circ}$.



				Reflector Specif	ications			
Part number	Price	Drawing Link	Quantity	Dimensions mm [in]	Degree of Protection	Mounting	Materials	
<u>RL102</u>	\$38.00	PDF	10	25				
<u>RL102-1</u>	\$4.25		1	[0.98]				
<u>RL103</u>	\$42.50	PDF	10	34.5		Customer-supplied adhesive or other		
<u>RL103-1</u>	\$4.75		1	[1.36]		mounting method required		
<u>RL104</u>	\$42.50		10	46		roquiou		
<u>RL104-1</u>	\$4.75	<u>PDF</u>	1	[1.81]			Reflective face: PMMA	
<u>RL105G</u>	\$38.00	DDE	10	95 x 38		Tue 4.2 mm holis	Polymethylmethacrylate (acrylic)	
<u>RL105G-1</u>	\$4.25	<u>PDF</u>	1	[3.74 x 1.50]		Two 4.3 mm holes	Base material: ABS	
<u>RL106G</u>	\$42.50	PDF	10	182 x 42		Two 6mm holes	(Acrylonitrile-butadiene-styren)	
<u>RL106G-1</u>	\$4.75		1	[7.17 x 1.65]				
<u>RL110</u>	\$19.00		10	84				
<u>RL110-1</u>	\$2.00	<u>PDF</u>	1	[3.31]	LEC IP67	One 5mm hole		
<u>RL116</u>	\$19.00		10	41 x 60		T. J. David halves		
<u>RL116-1</u>	\$2.00	<u>PDF</u>	1	[3.54 x 2.36]		Two 3mm holes		
<u>RL100DA4</u>	\$38.50	NA	1	200 x 300 [7.87 x 11.81]				
<u>RL100DC4</u>	\$12.00	NA	1	50 x 300 [1.97 x 11.81]		Self-adhesive	Paper (Acrylic tape with micro prism)	
<u>RL100DQ1</u>	\$8.75	NA	1	100 x 100 [3.94 x 3.94]				
<u>RL111G</u>	\$60.00	DDE	10	22.5 x 47				
<u>RL111G-1</u>	\$7.25	PDF	1	[0.89 x 1.85]		Two 3mm slots	Reflective face: PMMA	
<u>RL112G</u>	\$44.00	PDF	10	19 x 73			Polymethylmethacrylate (acrylic)	
<u>RL112G-1</u>	\$4.75		1	[0.75 x 2.87]			Base material: ABS	
<u>RL113G</u>	\$53.00	- PDF	10	51.4 x 60.3		Two 4mm slots	(Acrylonitrile-butadiene-styren)	
<u>RL113G-1</u>	\$6.00		1	[2.02 x 2.37]				

Not recommended for applications involving moist air environments or water immersion.

1-800-633-0405 **Reflectors**

RL Series Reflectors for Polarized Reflective Laser Photoelectric Sensors (FALN series)

Suitable for use with polarized light laser photoelectric sensors

- Sizes for most applications
- Miniature types for close mounting in multiple sensor installations
- Single and 5-packs available

Specifications									
Part Number	<u>RL201</u>	<u>RL201-1</u>	<u>RL203</u>	<u>RL203-1</u>	<u>RL204</u>	<u>RL204-1</u>			
Price	\$38.00	\$8.25	\$35.50	\$7.75	\$30.00	\$6.75			
Quantity	5	1	5	1	5	1			
Drawing Link	PE	<u>DF</u>	PDF		PDF				
Dimensions	60 x 8 2.36 x		19 x 6mm 0.75 x 2.36 in		20mm x 32mm 0.80 in x 1.26 in				
Degree of Protection ¹			IEC	IP67					
Mounting	Two 0.4 mm holes Two 0.4 mm holes Two 0.3 m				mm holes				
Materials			Acrylic/pol	ycarbonate					

¹ Not recommended for applications involving moist air environments or water immersion.