## Por the latest prices, please cneck Automatic PMW Series Inductive Proximity Sensors



### M12 (12mm) Stainless Steel – DC

- Low cost/high performance
- LED status indicators are visible at a wide angle.
- Axial cable or M12 quick-disconnect models
- Purchase cable separately (for quick-disconnect models).
- Lifetime warranty



PMW Series M12 DC Inductive Proximity Selection Chart									
Part Number	Price	Sensing Range	Mounting	Output State	Logic	Connection	Wiring	Dimensions	
Standard Distance									
<u>PMW-0N-1H</u>	\$46.50	2mm [0, 09 in]	Fluch		NPN	M12 [12mm] connector	Diagram 3	Figure 1	
<u>PMW-0P-1H</u>	\$46.50	2mm [0.08 in]	Flush	N.O./N.C.	PNP	M12 [12mm] connector	Diagram 4	Figure 1	
<u>PMW-0N-2H</u>	\$46.50	4 mm [0, 4 5 7 in]	Non-flush	N.O./N.C.	NPN	M12 [12mm] connector	Diagram 3	Figure 1	
<u>PMW-0P-2H</u>	\$46.50	4mm [0.157 in]			PNP	M12 [12mm] connector	Diagram 4	Figure 1	
Triple Distance									
PMW-AN-5A	\$111.00				NPN	2m [6.5 ft] axial cable	Diagram 1	Figure 2	
PMW-AP-5A	\$111.00	6mm [0 226 in]	Flush	NO	PNP	2m [6.5 ft] axial cable	Diagram 2	Figure 2	
PMW-AN-5H	\$111.00	6mm [0.236 in]	Flush	N.O.	NPN	M12 [12mm] connector	Diagram 1	Figure 3	
PMW-AP-5H	\$111.00				PNP	M12 [12mm] connector	Diagram 2	Figure 3	

### Wiring Diagrams

Diagram 1 NPN Output




Diagram 3 NPN Output





Diagram 2 PNP Output




Connector M12 connector



Note: Pin 2 is not present on some models.

Diagram 4 PNP Output



# Por the latest prices, please check Automatic PMW Series Inductive Proximity Sensors

PMW Series M12 DC Inductive Proximity Specifications						
Models	Standard Distance	Triple Distance				
Mounting Type	Flush	Flush				
Nominal Sensing Distance	2mm [0.08 in] <sup>1</sup>	6mm [0.236 in]				
Operating Distance	Ν	A				
Material Correction Factors	See the Material influence table					
Output Type	NPN or PNP and N.O./N.C. complementary	NPN or PNP, N.O. only				
Operating Voltage	10 to 3	0 VDC				
No-load Supply Current	≤15 mA	≤10 mA				
Operating (Load) Current	≤100 mA	≤ 00 mA				
Off-state (Leakage) Current	≤1 0µA	≤100µA				
Voltage Drop	≤1.2 V	≤2.0 V				
Switching Frequency	2kHz	400Hz				
Differential Travel (% of Nominal Distance)	2 to 10%	≤ 15%				
Repeat Accuracy	≤5%					
Ripple	≤10%	≤ 20%				
Time Delay Before Availability (tv)	100ms	≤10 ms				
Reverse Polarity Protection	Yes					
Short-circuit Protection	Yes					
Operating Temperature / Temperature Drift	-25 to 70°C [-13 to 158°F] / 10%Sr					
Protection Degree (DIN 40050)	IEC IP67/68	IEC IP67 <sup>2</sup> (connector/IP68 <sup>2</sup> cable)				
Indication/Switch Status	Yellow (N.O. ou	tput energized)				
Housing Material	Stainless steel	Stainless steel				
Sensing Face Material	PPS	Stainless steel				
Shock/Vibration	See Proximity Se	nsor Terminology				
Tightening Torque	10Nm [7.25 lb-in]					
Weight	35g [1.23 oz]	89g [3.14 oz]				
Connections	M12 connector with gold-plated contacts					
Agency Approvals	NA	UL file E328811, RoHS				


Notes: 1With 12 x 12mm FE360 target


<sup>2</sup>Fully submersible to 290 psi.

To obtain the most current agency approval information, see the Agency Approval Checklist section on the specific part number's web page.

#### Dimensions

mm[inches]








Figure 3

Note: Pin 2 is not present on some models.




Figure 4

# Accessories for 12mm Sensors

#### **Axial Mounting Bracket**

Mounting bracket, axial, available in zinc-plated steel or 316L stainless steel. For use with 12mm sensors. Has two mounting holes (use 3mm screws) and allows the rotation of an optical axis for right-angle adapter sensors. Hexagonal nuts not included.

Accessories for 12mm Sensors						
Part Number	Price	Drawing Link	Weight Ib [g]			
<u>ST12A</u>	\$2.00	Micro Detectors mounting bracket, axial, zinc plated steel. For use with 12mm sensors.	PDF	0.03 [13.6]		
<u>ST12A7W</u>	\$7.25	Micro Detectors mounting bracket, axial, 316L stainless steel. For use with 12mm sensors.	PDF	0.03 [13.6]		



<u>ST12A</u>

## **Right-angle Mounting Bracket**

Mounting bracket, right-angle, zinc-plated steel or 316L stainless steel. For use with 12mm sensors. Has two mounting holes (use 3mm screws) and allows the rotation of an optical axis for axial sensors. Hexagonal screws not included.

	Accessories for 12mm Sensors							
Part Number	Drawing Link	Weight Ib [g]						
<u>ST12C</u>	\$2.00	Micro Detectors mounting bracket, right-angle, zinc plated steel. For use with 12mm sensors.	<u>PDF</u>	0.03 [13.6]				
<u>ST12C7W</u>	\$7.25	Micro Detectors mounting bracket, right-angle, 316L stainless steel. For use with 12mm sensors.	<u>PDF</u>	0.03 [13.6]				



<u>ST12C</u>

# Accessories for 12mm Sensors

#### **Right-angle Mounting Brackets**

Mounting bracket, right-angle, fixed insertion stop adjustment, plastic. For use with 12mm sensors. Available with or without fixed insertion stop.

	Accessories for 12mm Sensors							
Part Number	Price	Description	Drawing Link	Weight Ib [g]				
<u>OPT2102</u>	\$8.00	Wenglor mounting bracket, right-angle, fixed insertion stop adjustment, plastic. For use with 12mm sensors.	PDF	0.05 [22.7]				
<u>OPT2103</u>	\$8.00	Wenglor mounting bracket, right-angle, plastic. For use with 12mm sensors.	<u>PDF</u>	0.05 [22.7]				



## **Right-angle Swivel Mounting Systems**

Mounting bracket, right-angle swivel, 360 degree vertical and horizontal adjustment, 12mm rod mount. For use with 12mm sensors. Available in all stainless steel or with an aluminum head and stainless steel mounting plate.

	Accessories for 12mm Sensors							
Part Number	Price	Description	Mounting Head	Mounting Plate	Drawing Link	Weight Ib [g]		
<u>OPT2114</u>	\$11.50	Wenglor mounting bracket, right-angle swivel, 360 degree vertical and horizontal adjustment, aluminum, 12mm rod mount. For use with 12mm sensors.	Aluminum	Stainless steel	<u>PDF</u>	0.14 [63.5]		
<u>OPT2115</u>	\$21.00	Wenglor mounting bracket, right-angle swivel, 360 degree vertical and horizontal adjustment, 304 stainless steel, 12mm rod mount. For use with 12mm sensors.	304 Stainless steel	304 Stainless steel	<u>PDF</u>	0.27 [122.5]		



Note: 304 stainless steel mounting rods sold separately: <u>OPT2109</u> (200mm [7.87 in] length), <u>OPT2110</u> (300mm [11.81 in] length), and <u>OPT2111</u> (500mm [19.69 in] length).

OPT2114, OPT2115

## 1-800-633-0405 Mounting Rods and Brackets

#### **Mounting Rods**

304 Stainless steel rods for mounting swivel brackets <u>OPT2112</u> - <u>OPT2127</u> Available in three lengths: 200mm, 300mm, and 500mm. 12mm diameter.

M	Mounting Rods for OPT2112-2127 Swivel Mounting Brackets							
Part Number	Part Number Price Description		Drawing Link	Weight Ib (g)				
<u>OPT2109</u>	\$13.00	Wenglor mounting rod, 12mm diameter, 200mm length, 304 stainless steel.	PDF	0.41 [185.97]				
<u>OPT2110</u>	\$16.00	Wenglor mounting rod, 12mm diameter, 300mm length, 304 stainless steel.	PDF	0.60 [272.16]				
<u>OPT2111</u>	\$21.00	Wenglor mounting rod, 12mm diameter, 500mm length, 304 stainless steel.	PDF	0.98 [444.52]				



## **Right-angle Mounting Bracket**

Mounting bracket, right-angle, nickel-plated brass. For use with 12mm mounting rods <u>OPT2109</u>, <u>OPT2110</u> & <u>OPT2111</u>.

	Right-angle Mounting Brackets for 12mm Sensors								
Part Number	Part Number Price Description			Weight Ib [g]					
<u>OPT2108</u>	\$16.00	Wenglor mounting bracket, right-angle, nickel-plated brass. For use with 12mm mounting rods OPT2109, OPT2110 & OPT2111.	<u>PDF</u>	0.07 [31.8]					

