SU Series Ultrasonic Sensors



M18 (18mm) Plastic – PNP or Analog Output

- High resolution
- 2 analog models available
- Complete overload protection
- IP67 rated
- Purchase cable separately (for quick-disconnect model)



SU Series Ultrasonic Analog Output Sensor Selection Chart						
Part Number Price		Sensing Range	Output	Connection	Wiring	
SU1-B1-0E	\$317.00	100 to 600 mm [3.94-23.62 in]	0-10 VDC	M12 [12mm] connector	Diagram 2	
SU2-A1-0E	\$346.00	200 to 1500 mm [7.87-59.06 in]	0-10 VDC	M12 [12mm] connector	Diagram 2	


Specifications Specification Specificati						
Mounting Type	<u>SU1-B1-0E</u>	<u>SU2-A1-0E</u>				
Nominal Sensing Distance	100 to 600 mm [3.94-23.62 in]	200 to 1500 mm [7.87-59.06 in]				
Operating Distance	N/	'A				
Output Type	0-10	VDC				
Operating Voltage	18-30	VDC				
No-load Supply Current	≤ 35	mA				
Operating (Load) Current	≤ 5	mA				
Off-state (Leakage) Current	≤ 10	μΑ				
Voltage Drop	-	-				
Switching Frequency	N.	A				
Differential Travel	-	-				
Repeat Accuracy	±2 r	mm				
Time Delay Before Availability (tv)	≤ 50	0ms				
Reverse Polarity Protection	Ye	es				
Short-Circuit Protection	Yes (switch auto-resets a	fter overload is removed)				
Linearity Error	≤ 0.	3%				
Ultrasonic Frequency	300kHz	180kHz				
Ultrasonic Beam Angle	8	0				
Max. Response Time	50ms	150ms				
Control Input	Hold /	Sync				
Sensitivity Adjustment	-					
Input Voltage Transient Protection	Yes, only if transient peak	does not exceed 30 VDC				
Operating Temperature	-25 to +70°C [[-13 to 158°F]				
Temperature Compensation	Ye	es				
Protection Degree	IEC I	P67				
Indication/Switch Status	-					
Housing Material	Polybutylene Tere	ephthalate [PBT]				
Shock/Vibration	See Proximity Se	nsor Terminology				
Tightening Torque	3 Nm [2.	21 lb-ft]				
Weight	38g [1.	34 oz]				
Connection	M12 [12 mm	n] connector				
Agency Approvals	CE, UL listed					

To obtain the most current agency approval information, see the Agency Approval Checklist section on the specific part number's web page.

SU Series Ultrasonic Sensors


Dimensions

mm [inches]




Wiring Diagrams










Connector



Must be used with 2M or 7M cable (4-wire)


Characteristic Curves

Analog Output




Distance (mm)

Detection Area SU1 Analog output



Detection Area SU2 Analog output



^{*}Note: Control wire can be used to inhibit sensor or to synchronize with another sensor.

Accessories for 18mm Sensors

Axial Mounting Bracket

Axial mounting bracket available in zinc plated steel or 316L stainless steel. Has two mounting holes (use 4mm screws) and allows for rotation of an optical axis for right-beam-angle-adapter sensors. Hexagonal nuts not included. For use with 18mm sensors.


Accessories for 18mm Sensors					
		Weight lb [g]			
<u>ST18A</u>	\$2.00	Micro Detectors mounting bracket, axial, zinc plated steel. For use with 18mm sensors.	0.06 [27.2]		
<u>ST18A7W</u>	\$7.25	Micro Detectors mounting bracket, axial, 316L stainless steel. For use with 18mm sensors.	0.06 [27.2]		



ST18A

Dimensions

mm [inches]



Right-angle Mounting Bracket


Right-angle mounting bracket for use with 18mm sensors. Has two mounting holes (use 4mm screws) and allows the rotation of an optical axis for axial sensors. Hexagonal nuts not included.

Accessories for 18mm Sensors					
Part Nilmner Price liescrintion		Weight lb [g]			
ST18C	\$2.00	Micro Detectors mounting bracket, right-angle, zinc plated steel. For use with 18mm sensors.	0.06 [27.2]		
<u>ST18C7W</u>	\$7.25	Micro Detectors mounting bracket, right-angle, 316L stainless steel. For use with 18mm sensors.	0.06 [27.2]		



Dimensions

mm [inches]



Accessories for 18mm Sensors

Right-angle Mounting Brackets

Mounting bracket, right-angle, fixed insertion stop adjustment, plastic. For use with 18mm sensors. Available with or without fixed insertion stop.

Accessories for 18mm Sensors							
Part Number	Price	Description Drawing Link		Weight lb [g]			
<u>OPT2104</u>	\$10.50	Wenglor mounting bracket, right-angle, fixed insertion stop adjustment, plastic. For use with 18mm sensors.	PDF	0.06 [27.2]			
<u>OPT2105</u>	\$10.50	Wenglor mounting bracket, right-angle, plastic. For use with 18mm sensors.	<u>PDF</u>	0.06 [27.2]			



OPT2104, OPT2105

Right-angle Swivel Mounting Systems

Mounting bracket, right-angle swivel, 360 degree vertical and horizontal adjustment, 12mm rod mount. For use with 18mm sensors. Available in all 304 stainless steel or with an aluminum head and a stainless steel mounting plate.

Accessories for 18mm Sensors							
Part Number	Price	Description	Mounting Head	Mounting Plate	Drawing Link	Weight lb [g]	
<u>OPT2116</u>	\$11.50	Wenglor mounting bracket, right-angle swivel, 360 degree vertical and horizontal adjustment, aluminum, 12mm rod mount. For use with 18mm sensors.	Aluminum	304 Stainless steel	<u>PDF</u>	0.15 [68.0]	
<u>OPT2117</u>	\$21.00	Wenglor mounting bracket, right-angle swivel, 360 degree vertical and horizontal adjustment, 304 stainless steel, 12mm rod mount. For use with 18mm sensors.	304 Stainless steel	304 Stainless steel	<u>PDF</u>	0.28 [127.0]	



OPT2116, OPT2117

Note: 304 Stainless steel mounting rods sold separately: <u>OPT2109</u> (200mm [7.87 in] length), <u>OPT2110</u> (300mm [11.81 in] length), and <u>OPT2111</u> (500mm [19.69 in] length).

Mounting Rods and Brackets

Mounting Rods

304 Stainless steel rods for mounting swivel brackets <u>OPT2112</u> - <u>OPT2127</u> Available in three lengths: 200mm, 300mm, and 500mm. 12mm diameter.

Mounting Rods for OPT2112-2127 Swivel Mounting Brackets						
Part Number	Price	Description	Drawing Link	Weight Ib (g)		
<u>OPT2109</u>	\$13.00	Wenglor mounting rod, 12mm diameter, 200mm length, 304 stainless steel.	PDF	0.41 [185.97]		
<u>OPT2110</u>	\$16.00	Wenglor mounting rod, 12mm diameter, 300mm length, 304 stainless steel.	PDF	0.60 [272.16]		
<u>OPT2111</u>	\$21.00	Wenglor mounting rod, 12mm diameter, 500mm length, 304 stainless steel.	PDF	0.98 [444.52]		



Right-angle Mounting Bracket

Mounting bracket, right-angle, nickel-plated brass. For use with 12mm mounting rods OPT2109, OPT2110 & OPT2111.

Right-angle Mounting Brackets for 12mm Sensors						
Part Number Price Description		Drawing Link	Weight lb [g]			
<u>OPT2108</u>	\$16.00	Wenglor mounting bracket, right-angle, nickel-plated brass. For use with 12mm mounting rods OPT2109, OPT2110 & OPT2111.	<u>PDF</u>	0.07 [31.8]		

