



MURRELEKTRONIK ANALOG INPUT CONVERTER, 1-CHANNEL, CURRENT/VOLTAGE, 15-BIT, INPUT CURRENT SIGNAL RANGE(S) OF 0-20 mA, 4-20 mA, INPUT SIGNAL VOLTAGE RANGE(S) OF +/- 10 VDC, 0-10 VDC, IO-LINK CLASS A DEVICE, IO-LINK v1.1, IP65, IP67

5000-00501-1300001

AutomationDirect.com
1-800-633-0405



3rd
ANGLE

NOT TO
SCALE

PART DIMENSIONS MAY DIFFER SLIGHTLY
DUE TO MANUFACTURER'S VARIANCES

METRIC UNITS USED
FOR PART DESIGN

UNLESS OTHERWISE
SPECIFIED UNITS ARE:

mm
[inch]

LATEST VERSION
11/15/2022

SHEET 1 OF 1