



MURRELEKTRONIK ANALOG OUTPUT CONVERTER, 1-CHANNEL, CURRENT/VOLTAGE, 15-BIT, OUTPUT CURRENT SIGNAL RANGE(S) OF 0-20 mA & 4-20 mA, OUTPUT VOLTAGE RANGE(S) OF +/- 10 VDC & 0-10 VDC, IO-LINK CLASS A DEVICE, IO-LINK v1.1, IP65, IP67

5000-00501-2300001

AutomationDirect.com  
1-800-633-0405



3rd  
ANGLE

NOT TO  
SCALE

PART DIMENSIONS MAY DIFFER SLIGHTLY  
DUE TO MANUFACTURER'S VARIANCES

METRIC UNITS USED  
FOR PART DESIGN

UNLESS OTHERWISE  
SPECIFIED UNITS ARE:

mm  
[inch]

LATEST VERSION  
11/15/2022

SHEET 1 OF 1