



LS ELECTRIC MEDIUM INERTIA AC BRUSHLESS SERVO MOTOR, 2.2 kW, 3-PHASE, INTEGRATED BRAKE, FOR USE WITH L7PA020U-AD 2 kW DRIVE

APM-FE22DMK2

AutomationDirect.com
 1-800-633-0405



3rd
 ANGLE

NOT TO
 SCALE

PART DIMENSIONS MAY DIFFER SLIGHTLY
 DUE TO MANUFACTURER'S VARIANCES

METRIC UNITS USED
 FOR PART DESIGN

UNLESS OTHERWISE
 SPECIFIED UNITS ARE:

mm
 [inch]

LATEST VERSION
 8/17/2022

SHEET 1 OF 1