


LENK Model WG991KCS DUAL HEAT SOLDERING GUN KIT 150/100 Watts, 120 Volts

FEATURES:

- **3-Position Trigger Control** (High, Low or Off) provides excellent control of tip heat for more precise soldering.
- **Provides Tip Temperatures up to 800° F.**, allows for greater flexibility in soldering, cutting or smoothing functions.
- **Large 1-Finger Trigger Switch** is conveniently located for optimum heat control and comfort.
- **Tip Heats up in Less than 10 Seconds**, use of the tool is almost instantaneous and wait time is minimal.
- **Quick-Change Type Tips** can be easily and quickly changed within 30 seconds.
- **Three Different Tips** (Soldering, Cutting, And Smoothing) provide versatility.
- **Balanced Tool Design** is more comfortable and easier to use.
- **Built-In Spotlight** automatically illuminates the work area for improved visibility.
- **Integral Tool Stand** keeps heated part of tool out of harm's way.
- **UL Listed**

HOW TO SOLDER

1. **Use the correct tool.** Wattage and tip size should be sufficient to thoroughly heat the parts being soldered.
2. **Use the proper solder.**
3. **Clean the work** thoroughly to ensure good bond using steel wool, fine sandpaper or file. Clean printed circuit boards gently.
4. **"Tin" tip of tool.** As tool heats up, apply solder to tip surfaces.
5. **Heat the work surface** thoroughly using entire tip surface. Then apply solder to heated parts at the point of tip contact. Don't over solder.
6. **Allow solder to cool and set** before moving parts.
7. **MAINTAIN TOOL FOR LONGER LIFE**
 - a. Clean tip with steel wool or a fine file.
 - b. Always keep tip well "linned".
 - c. During use, check to make sure the connector screws remain tight by occasionally retightening with screwdriver.
 - d. Where tip and gun connectors touch and overlap, keep the areas clean for best results.



⚠ DANGER

- Do not immerse in water. Could cause ELECTRICAL SHOCK To do so could cause you or serious injury or damage to the tool.
- This tool has a polarized plug. To reduce the risk of electric shock, this plug is intended to fit in a polarized outlet only one way. If the plug does not fit fully into the outlet, reverse the plug. If it still does not fit, contact a qualified electrician. Do not modify the plug in any way.
- This tool gets very HOT and can cause severe burns. When using, touch the handle only. DO NOT touch any metal parts.
- The tool is not a toy. KEEP AND STORE OUT OF REACH OF CHILDREN.
- ADEQUATE VENTILATION must be used at all times.
- To prevent fires, keep the tool and tool holder away from all combustible materials.



Designed for intermittent use.
Duty cycle: "ON" for 1 min., "OFF" for 4 mins.

⚠ WARNING

- For safety, unplugging the unit when not in use.
 - Allow to cool to room temperature before placing the tool in storage (allow 1-2 hours).
 - If a separate tool holder is used, always use a pair of pliers to move the tool holder, as the holder can become hot while it holds the tool. Always use pliers to change tips.
 - This product when used for soldering or similar applications, can expose you to chemicals including lead known to the State of California to cause cancer and birth defects (or other reproductive harm). For more information, go to www.P65Warnings.ca.gov.
- Note: Lead-free solder is recommended.**

LIMITED GUARANTEE

Wall Lenk Corporation warrants its products and accessories to be free from defective materials and workmanship for five years from date of original purchase. This warranty does not apply to any product which has been disassembled, damaged or defaced, subjected to misuse, abnormal service and mishandling, nor any product altered, repaired, or disassembled by anyone other than Wall Lenk Corporation. During this warranty period Wall Lenk Corporation, at its option, may repair or replace such product at no cost to the purchaser for labor and/or materials when returned with transportation costs pre-paid to Wall Lenk Corporation, together with proof of purchase. THIS WARRANTY IS THE ONLY WARRANTY APPLICABLE TO WALL LENK CORPORATION'S PRODUCTS AND ACCESSORIES AND IS EXPRESSLY IN LIEU OF ANY AND ALL OTHER WARRANTIES, EXPRESSED OR IMPLIED, INCLUDING ANY IMPLIED WARRANTY OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE. THE WALL LENK CORPORATION SHALL NOT BE LIABLE FOR CONSEQUENTIAL OR INCIDENTAL DAMAGES RESULTING FROM BREACH OF WARRANTY. THE REMEDIES EXPRESSLY SET FORTH HEREIN ARE EXCLUSIVE AND NO OTHER REMEDY FOR BREACH OF WARRANTY EXISTS.



Wall Lenk Corporation

PO Box 3349
252-527-4186

Kinston, N.C. 28502-3349
Fax 252-527-4189