## **Proximity Sensor Damping Magnets**

## Magnet

Damping Magnets						
Part Number	Price	Drawing Link				
AW-MAG	\$097n:	PDF				
AW-MAG-3	\$11ha:	PDF				
<u>MAG-1</u>	\$11h6:	PDF				
MAG-3	\$11h7:	PDF				
MAG-4	\$11h8:	PDF				
MAG-5	\$11h9:	PDF				

- Damping magnet for use with magnet series sensors
- Barium ferrite and Samarium



Damping Magnets Specifications								
	<u>AW-MAG</u>	AW-MAG-3	<u>MAG-1</u>	<u>MAG-3</u>	<u>MAG-4</u>	<u>MAG-5</u>		
Ambient Temperature	-13 to 266°F [-25 to 130°C]	-13 to 266°F [-25 to 130°C]	-58 to 392°F [-50 to 200°C]		-13 to 392°F [-25 to 200°C]			
Housing Materials	Barium ferrite, samarium	Barium Ferrite	Samarium Cobalt	Barium Ferrite				
Coating	Stainless steel (1.4571/316Ti)		_	_	_	_		
Magnetic Field Strength	48 mT	45 mT	136 mT	95 mT	103 mT	115 mT		
Weight	82g [2.89 oz]	22g [0.78 oz]	4g [0.14 oz]	11g [0.39 oz]	35g [1.23 oz]	56g [1.98 oz]		

www.automationdirect.com