

# BZ0TKUAB Cut Sheet



Fuji Electric short circuit alarm contact, (1) N.O./(1) N.C. contact(s), 6A @ 120 VAC/1.1A @ 120 VDC. For use with BM3R/BM3V series manual motor protector.

For complete product information, please see this item on our store at the following link:



<https://www.automationdirect.com/pn/BZ0TKUAB>

## Technical Specifications

Brand	Fuji Electric
Item	Short circuit alarm contact
Contact Type	(1) N.O./(1) N.C.
Amperage Rating	6A @ 120 VAC/1.1A @ 120 VDC
For Use With	BM3R/BM3V series manual motor protector
Additional Information	Both contacts operate ONLY when the MMS trips due to a short circuit. The alarm contact is not linked to the ON/OFF operation. The power to the MMS can be turned ON after pressing the blue reset button on the alarm contact. Required when using the MMS in a UL Type E application

## Agency Approvals

UL Listed File #	E163944
UL Recognized File #	None
UL Hazardous File #	None
CE	<a href="#">View CE declarations</a>
RoHS Status	Yes (See CE Doc)
EU REACH	<a href="#">View EU REACH document</a>