

BZ0TKUAB Cut Sheet



Fuji Electric short circuit alarm contact, (1) N.O./ (1) N.C. contact(s), 6A @ 120 VAC/1.1A @ 120 VDC. For use with BM3R/BM3V series manual motor protector.

For complete product information, please see this item on our store at the following link:



<https://www.automationdirect.com/pn/BZ0TKUAB>

Technical Specifications

| | |
|-------------------------------|--|
| Brand | Fuji Electric |
| Item | Short circuit alarm contact |
| Contact Type | (1) N.O./ (1) N.C. |
| Amperage Rating | 6A @ 120 VAC/1.1A @ 120 VDC |
| For Use With | BM3R/BM3V series manual motor protector |
| Additional Information | Both contacts operate ONLY when the MMS trips due to a short circuit. The alarm contact is not linked to the ON/OFF operation. The power to the MMS can be turned ON after pressing the blue reset button on the alarm contact. Required when using the MMS in a UL Type E application |

Agency Approvals

| | |
|-----------------------------|--|
| UL Listed File # | E163944 |
| UL Recognized File # | None |
| UL Hazardous File # | None |
| CE | View CE declarations |
| RoHS Status | Yes (See CE Doc) |
| EU REACH | View EU REACH document |