

# SC-E5-100V Cut Sheet



Fuji Electric SC-E5 series IEC contactor, 105A, (3) N.O. power poles, (2) N.O./ (2) N.C. auxiliary contacts, 120 VAC (60Hz)/110 VAC (50Hz) coil voltage, low consumption electronic.

For complete product information, please see this item on our store at the following link:



<https://www.automationdirect.com/pn/SC-E5-100V>

## Technical Specifications

<b>Brand</b>	Fuji Electric
<b>Item</b>	Contactor
<b>Series</b>	SC-E5
<b>Contactor Type</b>	IEC
<b>Actuator Type</b>	Magnetic
<b>Amperage Rating</b>	105A
<b>Power Poles</b>	(3) N.O.
<b>Auxiliary Contacts</b>	(2) N.O./ (2) N.C.
<b>Coil Voltage</b>	120 VAC (60Hz)/110 VAC (50Hz)
<b>Coil Type</b>	Low consumption electronic

## Agency Approvals

<b>UL Listed File #</b>	E42419
<b>UL Recognized File #</b>	E44592
<b>UL Hazardous File #</b>	None
<b>CE</b>	<a href="#">View CE declarations</a>
<b>RoHS Status</b>	Yes (See CE Doc)
<b>EU REACH</b>	<a href="#">View EU REACH document</a>