## XBF-HO02A Cut Sheet





LS Electric XGB counter input module, 200 kHz maximum switching frequency, 2 high-speed input point(s), 5-24 VDC, sinking, 2-channel, single-ended encoder input(s), 2 high-speed output point(s), 5-24 VDC, sinking, external 24 VDC required.

For complete product information, please see this item on our store at the following link:



https://www.automationdirect.com/pn/XBF-HO02A

## **Technical Specifications**

| Brand   | LS Electric XGB    |
|---|--------------------|
| Item  | Input module       |
| I/O Module Type                               | Counter            |
| Maximum Switching<br>Frequency                | 200 kHz            |
| Number of High-Speed<br>Capable Input Points  | 2                  |
| Nominal Input Voltage                         | 5-24 VDC           |
| Discrete Input Type                           | Sinking            |
| Number of Non-Isolated Input Commons          | 1                  |
| <b>Number of Input Channels</b>               | 2                  |
| Encoder Input Type                            | NPN open collector |
| Number of High-Speed<br>Capable Output Points | 2                  |
| Nominal Output Voltage                        | 5-24 VDC           |
| Discrete Output Type                          | Sinking            |
| Number of Non-Isolated<br>Output Commons      | 1                  |

| Number of Isolated<br>Output Commons | 0  |
|--------------------------------------|--|
| Load Current                         | 0.1A/point   |
| High-Speed Counter(s)                | <ul> <li>up to (2) up counters</li> <li>up to (2) down counters</li> <li>up to (2) up/down counters</li> <li>up to (2) pulse/direction (bi-directional) counters</li> <li>up to (2) quadrature (A and B) counters</li> </ul> |
| Position Scaling                     | up to (2) up counters up to (2) down counters up to (2) up/down counters up to (2) up/down counters up to (2) pulse/direction (bi-directional) counters up to (2) quadrature (A and B) counters                              |
| Axis Profile(s)                      | linear mode     rotary mode  |
| External Power Requirement           | 24 VDC   |
| Requires                             | XTB-40H terminal block and C40HH-xxSB-XBI cable  |
| Programming Software                 | XG5000 programming software v4.7 or later  |

## Agency Approvals

| UL Listed File #     | E124950                |
|----------------------|------------------------|
| UL Recognized File # | None                   |
| UL Hazardous File #  | None                   |
| CE                   | View CE declarations   |
| CSA File #           | None                   |
| RoHS Status          | Yes (See CE Doc)       |
| EU REACH             | View EU REACH document |

## **Dimensional Drawings**



2D Drawing PDF Link: https://cdn.automationdirect.com/ /static/drawings/2d/XBF-HO02A.pdf See store item page for other formats.