

ZIPLink Accessories and Kits

Relay and fuse kits provide spare parts for ZIPLink fuse and relay modules.



ZL-RELAY-KIT



ZL-FUSE-KIT



ZL-CAPKIT

Kit	Description	Price
ZL-RELAY-KIT	CONTENTS: 10 spare relay spring clips for ZIPLink relay modules	<-->
ZL-FUSE-KIT	CONTENTS: 5A fuses - 3 pcs; 2A fuses - 7 pcs; Fuse covers for ZIPLink fuse modules 10 pcs.	<-->
ZL-CAPKIT	Capacitor for use with ZL-RS1-120 and ZL-RS4-120 relay modules when connected to the output of an AC triac device.	<-->



ZL-RELAY-120



ZL-RELAY-24

Note: See wiring details on our Web site at:

<http://www.automationdirect.com/static/manuals/ziplinks/ziplinks.html>

Specifications						
Relays	Part #	Pcs/Pkg	Price/Pkg	Part #	Pcs/Pkg	Price/Pkg
		ZL-RELAY-120	10	<-->	ZL-RELAY-24	10
Description	120VAC Relay*			24VDC Relay*, **		
Contact Type	1 Form C (SPDT)					
Approvals	UL,CUL,CE					
Coil						
Supply Voltage	120VAC (96-132VAC)			24VDC (19.2-26.4VDC)		
Frequency	50/60Hz			DC		
Current	11mA			22mA		
Contact						
Material	Ag/Ni					
Voltage	250VAC/30VDC					
Current	10A					
Maximum Switching Voltage	400VAC					
Maximum Power Resistive	AC 2500VA, DC 300W					
Maximum Power Inductive	AC 1500VA, DC 150W					
Minimum Load	100mA 5VDC					
Mechanical Data Life	10X10 ⁶ cycles					
Electrical Data Life	200X10 ⁶ cycles					
Operate/Release Time	15ms/10ms					
Environmental						
Coil to Contact Isolation	6kV (8mm)					
Operating Temperature	-40°C to +85°C					

* Replacement relays are Finder Series 40.31 at the time of the catalog printing. Compatible relay manufacturer may be substituted without notice.

** Replaces previous Omron Series G2R relay. See www.automationdirect.com/manuals for manufacture specifications.